

TriCaster® Specifications

	TriCaster® Mini Go	TriCaster® Mini X	TriCaster® Mini 4K	TriCaster® 410 Plus	TriCaster® TC1	TriCaster® 1 Pro	TriCaster® 2 Elite	TriCaster® Now	TriCaster® Vectar
Input Count	4	8	8	8	16	16	32	8	44
Input Types	IP/USB	IP/HDMI/USB	IP/HDMI*/USB	IP/SDI	IP/SDI	IP/SDI	IP/SDI	IP	IP
SDI I/O count	n/a	n/a	n/a	4	4	4	8	n/a	n/a
Output Mixes	2	4	4	4	4	4	8	4	8
DSK	2	2	2	2	4	4	4	2	4
M/E Count / Layer / Keys	2/2/2	4/2/2	4/2/2	4/2/2	4/4/4	4/4/4	8/4/4	4/2/2	8/4/4
Record Count	2	4	4	4	8	Unlimited	Unlimited	Unlimited	Unlimited
Max Session Res.	1080p/60	2160p/30	2160p/60	1080p/60	2160p/60	2160p/60	2160p/60	1080p/60	2160p/60
M/E Video Re-Entry	×	✓	✓	✓	✓	✓	✓	✓	✓
Live Call Connect	×	×	×	×	×	✓	✓	×	✓
Live Link	✓	✓	✓		✓	✓	✓	✓	✓
LivePanel	✓	✓	✓	✓**	✓**	✓	✓	✓	✓
Live Story Creator	×	✓	✓	✓**	✓**	✓	✓	✓	✓
NDI KVM	✓	✓	✓	✓	✓	✓	✓	✓	✓
Supplemental Audio	✓	✓	✓	✓**	✓**	✓	✓	✓	✓
Vertical Sessions	×	✓	✓	✓**	✓**	✓	✓	✓	✓
PSD Import Support	✓	✓	✓	✓	✓	✓	✓	✓	✓
AI Audio/Neural Voice Isolation	✓	✓	✓	✓	✓	✓	✓	✓	✓
NDI Matrix Router	×	×	×	×	×	✓	✓	×	✓
HDR Sessions & I/O	×	×	×	×	×	×	×	×	✓
Configurable I/O Connectors	×	×	×	×	×	×	×	×	×
AI Gaze Redirection	×	×	×	×	×	×	×	×	×
Programmable Outs	×	×	×	×	×	×	×	×	×